

AR V1.5 attenuation/gain control word

r1

Conn pin (J3)	4	5	6	8	10	12	14	11
Gain (dB)								Ground
-48	0	0	1	0	0	0	0	
-44	0	0	1	0	0	0	1	
-40	0	0	1	0	0	1	0	
-36	0	0	1	0	1	0	0	
-32	0	0	0	1	0	0	0	
-28	0	0	0	1	0	0	1	
-24	0	0	0	1	0	1	0	
-20	0	0	0	1	1	0	0	
-16	0	1	0	0	0	0	0	
-12	0	1	0	0	0	0	1	
-8	0	1	0	0	0	1	0	
-4	0	1	0	0	1	0	0	
0	1	0	0	0	0	0	0	
+4	1	0	0	0	0	0	1	
+8	1	0	0	0	0	1	0	
+12	1	0	0	0	1	0	0	

1 = +5V
0 = Gnd